

AX300 无线网卡 Linux 驱动源码 安装指南

一、安装须知

1、系统权限

在安装过程中需要获取 root 权限，出现下面显示后，需要输入该用户名所对应的密码，才会继续进行安装


```
[sudo] password for linn:
```

2、注意问题

先安装驱动，再插入网卡，如果先插入网卡，安装成功后需要重新拔插网卡

二、安装步骤


1、进入 `linux_driver_sourcecode/aic8800_linux_drvier` 目录后，右键打开终端 Terminal：



2、执行指令 “`sudo ./install_setup.sh`”，进行脚本准备。

```
指令: sudo ./install_setup.sh
```

执行成功显示如下：



3、切换到 `aic8800_linux_driver/drivers/aic8800` 目录下，执行指令“`make`”编译驱动

```
指令: make
```

驱动编译成功显示如下：

```
LD [M] /mnt/hgfs/share/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800/aic8800_fdrv/aic8800_fdrv.ko  
CC      /mnt/hgfs/share/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800/aic_load_fw/aic_load_fw.mod.o  
LD [M] /mnt/hgfs/share/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800/aic_load_fw/aic_load_fw.ko  
make[1]: Leaving directory '/usr/src/linux-headers-4.4.0-142-generic'  
/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800$
```

4、执行指令“`sudo make install`”加载驱动

指令：`sudo make install`

驱动加载成功显示如下：

```
linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800$ sudo make install  
mkdir -p /lib/modules/4.4.0-142-generic/kernel/drivers/net/wireless/aic8800  
install -p -m 644 aic_load_fw/aic_load_fw.ko /lib/modules/4.4.0-142-generic/kernel/drivers/net/wireless/aic8800/  
install -p -m 644 aic8800_fdrv/aic8800_fdrv.ko /lib/modules/4.4.0-142-generic/kernel/drivers/net/wireless/aic8800/  
/sbin/depmod -a 4.4.0-142-generic  
linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800$
```

5、将无线网卡插入电脑的 USB 接口，电脑识别到无线网卡后您就可以连接 WiFi 了。

三、驱动卸载

1、在驱动 `aic8800_linux_driver/drivers/aic8800` 目录下右键打开终端 Terminal，如下：



2、执行指令“`sudo rmmod aic8800_fdrv`”以及“`sudo rmmod aic_load_fw`”卸载 `aic8800_fdrv` 以及 `aic_load_fw` 模块（此时网卡一定要插在电脑上）

指令：`sudo rmmod aic8800_fdrv` 以及 `sudo rmmod aic_load_fw`

卸载模块成功如下显示：

```
linn@linn-virtual-machine:/mnt/hgfs/share/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800$ sudo rmmod aic8800_fdrv  
linn@linn-virtual-machine:/mnt/hgfs/share/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800$ sudo rmmod aic_load_fw  
linn@linn-virtual-machine:/mnt/hgfs/share/linux_driver_sourcecode/aic8800_linux_drvier/drivers/aic8800$
```

3、执行指令“`sudo make uninstall`”卸载驱动

指令：`sudo make uninstall`

卸载驱动成功如下显示：

四、注意事项

1、常见错误以及处理方法

问 1：无线网卡插入 Linux 主机的 USB 口后，系统识别显示 U 盘，怎么办？

执行命令“`mount`”查询识别U盘的名称（名称当中带 `aic`），查询到以后执行指令“`sudo eject /dev/sdc1`”弹出设备，其中“`/dev/sdc1`”表示U盘挂载在 `sdc1` 下，请根据实际输入，图片仅供参考。

指令: mount 以及指令: sudo eject /dev/sdc1

```
[...]
: $ sudo eject /dev/sdc1
```

问 2：无线系统异常，无法正常使用网卡怎么办？

执行指令“`sudo rfkill unblock wifi`”可以修复无线异常情况

指令: sudo rfkill unblock wifi

执行成功如下

```
:~/.Desktop$ sudo rfkill unblock wifi  
:~/.Desktop$
```

问 3：麒麟系统安装驱动的时候报错，无法正常安装驱动，怎么办？

缺环境造成的，执行指令“`sudo apt-get install build-essential`”，把该软件包安装好，再重新安装驱动即可。

指令： sudo apt-get install build-essential

报错如下显示：

```
install -p -m 644 aic_load_fw/aic_load_fw.ko /lib/modules/5.10.0-8-generic/kernel/drivers/net/wireless/aic8800/
install -p -m 644 aic8800_fdrv/aic8800_fdrv.ko /lib/modules/5.10.0-8-generic/kernel/drivers/net/wireless/aic8800/
/sbin/depmod -a 5.10.0-8-generic
insmod done
cc -c wifi_test.c -o wifi_test.o
wifi_test.c:1:10: fatal error: stdio.h: 没有那个文件或目录
 #include <stdio.h>
Compilation terminated.
make: *** [Makefile:16: wifi_test.o] 错误 1
make failed, install aic8800 wifi driver failed
dpkg: 处理软件包 ax300-wifi-adapter-linux-driver-v1.0.2 (--install)时出错:
```


2、辅助工具

1) 安装 ifconfig 网络工具

执行命令“`sudo apt install net-tools`”，安装 ifconfig 工具

指令：`sudo apt install net-tools`

安装成功如下显示：



```
$ sudo apt install net-tools
[sudo] password for linn:
Reading package lists... Done
Building dependency tree
Reading state information... Done
net-tools is already the newest version (1.60+git20180626.aebd88e-1ubuntu1).
0 upgraded, 0 newly installed, 0 to remove and 294 not upgraded.
```

2) 执行命令“ifconfig”进行查询。

3、网卡使用

在使用网卡的过程中，尽量不要在 SSID 或者密码中使用单引号等特殊字符，否则可能会出现扫描不到或者连接不上无线信号的情况。

4、常见的编译错误

1) 重定义错误

```
In file included from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_defs.h:32:0,
                  from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_tx.h:16,
                  from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_tx_c:13:
/home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_compat.h:278:8: 错误：'struct ieee80211_wmm_param_ie' 重定义
struct ieee80211_wmm_param_ie [
In file included from include/net/cfg80211.h:24:0,
```

此错误提示 `struct ieee80211_wmm_param_ie` 和内核头文件中 `cfg80211.h`

中的 struct ieee80211_wmm_param_ie 重定义。可以在内核头文件中查看结构体定义是否一致，如果一致的话，去掉驱动中的定义，如果不一致，根据内核中的定义来修改驱动。

```
277 //  
278 #if 0  
279 struct ieee80211_wmm_param_ie {  
280     u8 element_id; /* Element ID: 221 (0xdd); */  
281     u8 len; /* Length: 24 */  
282     /* required fields for WMM version 1 */  
283     u8 oui[3]; /* 00:50:f2 */  
284     u8 oui_type; /* 2 */  
285     u8 oui_subtype; /* 1 */  
286     u8 version; /* 1 for WMM version 1.0 */  
287     u8 qos_info; /* AP/STA specific QoS info */  
288     u8 reserved; /* 0 */  
289     /* AC_BE, AC_BK, AC_VI, AC_VO */  
290     struct ieee80211_wmm_ac_param ac[4];  
291 } __packed;  
292 #endif
```

2) 参数不一致

```
/home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_rx.c:978:13: 错误：提供给函数 'cfg80211_roamed' 的实参太多  
    GFP_ATOMIC);  
  
In file included from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_defs.h:20:0,  
from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_rx.c:14:  
include/net/cfg80211.h:5505:6: 附注：在此声明  
void cfg80211_roamed(struct net_device *dev, struct cfg80211_roam_info *info);  
  
/home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_rx.c: 在函数 'rwnx_rx_sm_disconnect_ind' 中:  
/home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_rx.c:1060:13: 错误：提供给函数 'cfg80211_disconnected' 的实参太少  
    cfg80211_disconnected(dev, ind->reason_code, NULL, 0);  
  
In file included from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_defs.h:20:0,  
from /home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_msg_rx.c:14:  
include/net/cfg80211.h:5521:6: 附注：在此声明  
void cfg80211_disconnected(struct net_device *dev, u16 reason);
```

此错误提示 cfg80211_roamed 参数太多及 cfg80211_disconnected 参数太少

①cfg80211_roamed 修改

查看 cfg80211.h 中 cfg80211_roamed 的函数声明，如下：

```
/**  
 * cfg80211_roamed - notify cfg80211 of roaming  
 *  
 * @dev: network device  
 * @info: information about the new BSS. struct &cfg80211_roam_info.  
 * @gfp: allocation flags  
 *  
 * This function may be called with the driver passing either the BSSID of the  
* new AP or passing the bss entry to avoid a race in timeout of the bss entry.  
* It should be called by the underlying driver whenever it roamed from one AP  
* to another while connected. Drivers which have roaming implemented in  
* firmware should pass the bss entry to avoid a race in bss entry timeout where  
* the bss entry of the new AP is seen in the driver, but gets timed out by the  
* time it is accessed in __cfg80211_roamed() due to delay in scheduling  
* rdev->event_work. In case of any failures, the reference is released  
* either in cfg80211_roamed() or in __cfg80211_roamed(), Otherwise, it will be  
* released while disconnecting from the current bss.  
*/  
void cfg80211_roamed(struct net_device *dev, struct cfg80211_roam_info *info,  
                      gfp_t gfp);
```

使用 uname -a 或者 uname -r 查看内核版本如下：

```
[aic@aic aic8800]# uname -a  
Linux aic 3.10.0-957.el7.x86_64 #1 SMP Thu Nov 8 23:39:32 UTC 2018 x86_64 x86_64 x86_64 GNU/Linux
```

当前内核版本为 3.10，根据代码，修改如下：

```
955     else {  
956         #if LINUX_VERSION_CODE >= KERNEL_VERSION(4, 12, 0) || CONFIG_CENTOS  
957             struct cfg80211_roam_info info;  
958             memset(&info, 0, sizeof(info));  
959             if (rwnx_vif->ch_index < NX_CHAN_CNTX_CNT)  
960                 info.channel = rwnx_hw->chanctx_table[rwnx_vif->ch_index].chan_def.chan;  
961             info.bssid = (const u8 *)ind->bssid.array;  
962             info.req_ie = req_ie;  
963             info.req_ie_len = ind->assoc_req_ie_len;  
964             info.resp_ie = rsp_ie;  
965             info.resp_ie_len = ind->assoc_rsp_ie_len;  
966             cfg80211_roamed(dev, &info, GFP_ATOMIC);  
967     }  
968     else {  
969         struct cfg80211_roam_info info;  
970         memset(&info, 0, sizeof(info));  
971         if (rwnx_vif->ch_index < NX_CHAN_CNTX_CNT)  
972             info.channel = rwnx_hw->chanctx_table[rwnx_vif->ch_index].chan_def.chan;  
973             info.bssid = (const u8 *)ind->bssid.array;  
974             info.req_ie = req_ie;  
975             info.req_ie_len = ind->assoc_req_ie_len;  
976             info.resp_ie = rsp_ie;  
977             info.resp_ie_len = ind->assoc_rsp_ie_len;  
978             cfg80211_roamed(dev, &info, GFP_ATOMIC);  
979     }  
980 }
```

②cfg80211_disconnected 修改

查看 cfg80211.h 中 cfg80211_disconnected 的函数声明

```
/**  
 * cfg80211_disconnected - notify cfg80211 that connection was dropped  
 *  
 * @dev: network device  
 * @ie: information elements of the deauth/disassoc frame (may be %NULL)  
 * @ie_len: length of IEs  
 * @reason: reason code for the disconnection, set it to 0 if unknown  
 * @locally_generated: disconnection was requested locally  
 * @gfp: allocation flags  
 *  
 * After it calls this function, the driver should enter an idle state  
 * and not try to connect to any AP any more.  
 */  
void cfg80211_disconnected(struct net_device *dev, u16 reason,  
                           const u8 *ie, size_t ie_len,  
                           bool locally_generated, gfp_t gfp);  
/**
```

当前内核版本为 3.10，根据代码，修改 rwnx_compat.h 如下：

```
207  
208 #if 0 // LINUX_VERSION_CODE < KERNEL_VERSION(4, 2, 0) && (!defined CONFIG_CENTOS)  
209 #define cfg80211_disconnected(dev, reason, ie, len, local, gfp) \  
210     cfg80211_disconnected(dev, reason, ie, len, gfp)  
211 #endif  
212
```

或者

```
208 #if LINUX_VERSION_CODE < KERNEL_VERSION(4, 2, 0)  
209 #define cfg80211_disconnected(dev, reason, ie, len, local, gfp) \  
210     cfg80211_disconnected(dev, reason, ie, len, local, gfp)  
211 #endif  
212
```

3) 未声明或者未定义

```
/home/aic/work/drivers/aic8800/aic8800_fdrv/rwnx_compat.h:205:27: 错误: IEEE80211_NUM_BANDS'未声明 [在此函数内第一次使用]
#define NUM_NL80211_BANDS IEEE80211_NUM_BANDS
```

此错误为未声明，查看内核头文件，已经存在 NUM_NL80211_BANDS 的声明

```
/*
 * enum nl80211_band - Frequency band
 * @NL80211_BAND_2GHZ: 2.4 GHz ISM band
 * @NL80211_BAND_5GHZ: around 5 GHz band (4.9 - 5.7 GHz)
 * @NL80211_BAND_60GHZ: around 60 GHz band (58.32 - 64.80 GHz)
 * @NUM_NL80211_BANDS: number of bands, avoid using this in userspace
 *                      since newer kernel versions may support more bands
 */
enum nl80211_band {
    NL80211_BAND_2GHZ,
    NL80211_BAND_5GHZ,
    NL80211_BAND_60GHZ,
    NUM_NL80211_BANDS,
};
```

解决方法：

```
203
204 #if LINUX_VERSION_CODE < KERNEL_VERSION(4, 7, 0)
205 #define NUM_NL80211_BANDS IEEE80211_NUM_BANDS
206 #endif
207
```